

# Manual SSD Waffler

## Operating Instructions



### Description

The Pure Leverage Waffler SSD Crusher Adapter is for destroying small "circuit board" devices such as SSD's, and thumb drives. It folds them every .25"/7mm in order to crack all memory chips.

The Waffler is designed for destroying M.2 and 2.5" Form Factor SSD modules. The goal is to "waffle" the circuit boards holding the data storage chips and to crack those chips, therefore protecting all data. The Waffler is recommended for SSDs with lengths less than 3"/80mm and thickness no greater than .625"/10mm. Common Workstation SSDs are perfect for destruction by the Pure Leverage Waffler. The SSD modules may NOT have any additional encasement or have heat syncs attached to them.

### Preparation for crushing SSD's

First, raise the spike by removing the clevis pin and position it on the lower set of holes. (1) This will allow the Waffler to fit into the tray of the Crusher. Next, insert Waffler into the tray of the Crusher. (2)



1. Position spike in lower holes



2. Insert Waffler into tray



3. Optional; Flip handle

**Optional;** to make the crushing processes easier; you may remove the long handle and flip it over. This will put the end of the handle lower and in a comfortable position for crushing. (See pic 3)



## Operation

Place the Pure Leverage Hard Drive Crusher on durable surface such as the floor or sturdy table.

Lift the handle and place the SSD into the Waffler from the front, or from the side. We recommend you experiment to see what works best for you. Slowly pull the handle straight down to prevent tipping.

Pull down until the SSD is cracked and bent to ensure all chips are cracked.

Remove Waffler and empty SSD and any debris.

## MAINTENANCE

May periodically LUBRICATE joints and pins to prevent wear.


Use thick lubricating grease every 500 crushes or when pins appear dry.

## SAFETY

Wear goggles and gloves. Small parts may fall from the drive during crushing. Be careful handling drives and debris to prevent injury. Small parts and broken drives may have sharp edges.

Do not use this machine for any other purpose. Do not carry without the handle in the latched down position, it could bend or break the guide, or cause injury.

Pure Leverage and their suppliers accept no culpability or liability by any entity for misuse or damages caused by this machine, for any reason, or any damage, loss or injury, physical, financial or emotional. Use this machine responsibly. In other words, be careful and use normal reasonable caution when in use, and when transporting this device. Be careful. Follow the instructions above. Use this device at your own risk.



Pure Leverage Hard Drive Crushers  
[www.purelev.com](http://www.purelev.com)  
[info@purelev.com](mailto:info@purelev.com)